

# MANUAL STROBE-LIGHT

720 PCS  
0,5W LEDS



SEGMENT  
CONTROL



POWERFUL  
EFFECT

















[WWW.LIGHT-INC.NL](http://WWW.LIGHT-INC.NL)

THANK YOU FOR PURCHASING OUR PRODUCTS.

Every unit has been thoroughly tested and has been shipped in perfect operating condition. Carefully check the outer and inner packaging for damage that may have occurred during shipping. If the carton appears to be damaged, carefully inspect your fixture for any damage and be sure all accessories necessary to operate the unit have arrived intact. In case damage has been found or parts are missing, please contact the distributor or your dealer for further instructions. Do not return this unit to your dealer without first contacting them.

## 1. SAFETY INFORMATION

	Before operating this unit, please carefully read this manual and keep for usage in the future. It is necessary to respect the following rules.
	Disposal of the device after its life cycle can damage the environment. Take it to a recycling company or return it to the authorized dealer.
	The products referred to in this manual conform to the guidelines of the European Community and are therefore marked with the CE logo.
	Keep this device away from children and unauthorized users. The dealer is not liable for damage as a result of ignoring the information in this manual and incorrect operation.
	Before operating this unit, please make sure the housing is in good condition and ensure pan and tilt can rotate in full range.
	Ensure that a minimum distance of 0.5 m is maintained between the fixture and any flammable material.
	The device can only function with 100-240v voltage, 50 / 60Hz power. Do not connect to any other power supply. Disconnect the device from the power supply before opening it or before maintenance.
	Never look directly into the projecting lens when the fixture is switched on. The light can cause epileptic seizures in light-sensitive people or people with epilepsy. Extreme caution and compliance with these safety instructions are required, especially with beam effects.
	Do not place or install the device on a surface that is exposed to vibration or any movement.
<b>-15°C + 45°C</b>	The device should operate in temperature range -15 °C and + 45 °C. Do not use the device if the temperature exceeds this range.
	The lens shield must be replaced if it is broken. Never use the device if the shield is not fully closed.
	Safety I class device must be earthed.
	When the fixture is mounted overhead, the safety rope must be attached to the correct mounting location on the bottom of the device.
	Please note that damage caused by manual changes to the device is not covered by the warranty.
	If possible, recycle all packaging material

## 2. DMX CHART

Channel	Function	DMX Value	Description
1	Dimmer	0-4	No effect
		5-255	From dark to light
2	Strobe	0-4	No effect
		5-255	From slow to fast
3	Macro Function	0-4	No effect
		5-89	Circular strobe effect
		90 -169	Fade in
		170-249	Fade out
		250-255	Sound
4	Effect speed	0-255	From slow to fast
5	Auto	5-255	Auto

## 3. LED DISPLAY

No.	Menu		Function Option
1	Address		001-512
2	Run Mod		Slve
			Auto
			Sond
3	ChanMod		5CH
4	DmxClea		Off
			On
5	Display	LightOff	Ligh
			1Min
			2Min
			3Min
		MenuBak	Off
			1Min
			2Min
			3Min
		LigtFlh	Off
			On

6	Balance	White1	50-255
		White2	
		White3	
		White4	
7	Manual	Dimming	0-255
		Speed	
		Case	
		Case Speed	
		Auto	
8	DefCfig		Off
			On
9	Version		Vxxx

#### 4. SPECIFICATIONS

- Light source: 720\*0.5W white LED
- Beam angle: 120°
- Segment control
- Life Time: 80.000 hours
- DMX Channels: 5
- Operation mode: DMX512, manual, sound, internal program
- IP Rating: indoor use only
- Power consumption: 300w
- Voltage 110V-240V 50/60Hz
- Power supply: built-in and auto switching
- Dimensions: 500x140x255mm (L\*W\*H)
- Weight: 4.5 KG







