



STROBE-LIGHT

Channel	Function	DMX Value	Description
1	Dimmer	0-4	No effect
		5-255	From dark to light
2	Strobe	0-4	No effect
		5-255	From slow to fast
3	Macro Function	0-4	No effect
		5-89	Circular strobe effect
		90 -169	Fade in
		170-249	Fade out
		250-255	Sound
4	Effect speed	0-255	From slow to fast
5	Auto	5-255	Auto

LCD

No.	Menu		function option
1	Address		001-512
2	Run Mod		Slve
			Auto
			Sond
3	ChanMod		5CH
4	DmxClea		Off
			On
5	Display	LigtOff	Ligh
			1Min
			2Min
			3Min
		MenuBak	Off
			1Min
			2Min
			3Min
		LigtFlh	Off
			On
6	Balance	White1	50-255
		White2	
		White3	
		White4	
7	Manual	Dimming	0-255
		Speed	
		Case	
		Case Speed	
		Auto	
8	DefCfig		Off
			On
9	Version		Vxxx